

# KATB-010A-CAV

CFC, R-12, 60 Hz, 1- Phase, 208/230 V  
Low Temperature

**Production Status:** This model is obsolete and is no longer in production for both OEM and service replacement. Please contact Customer Service about possible replacement models.

## Electrical Components

| External Protector        |                    |
|---------------------------|--------------------|
| Part No:                  | 071-0092-39        |
| Usage Description         |                    |
| <u>Vendor Part Number</u> | <u>Vendor Name</u> |
| CRA3787-18                | T I                |

| Stator      |             |            |      |
|-------------|-------------|------------|------|
| Part No:    | 046-2030-37 |            |      |
| Resistance: | +/-7%       | Start Wdg: | 4.53 |
|             |             | Run Wdg:   | 1.37 |

| Potential Relays          |                    |
|---------------------------|--------------------|
| Part No:                  | 040-0166-10        |
| Usage Description         |                    |
| <u>Vendor Part Number</u> | <u>Vendor Name</u> |
| RVA4AQ6D-920              | ELECTRICA          |

| Start Capacitor   |                 |           |        |
|-------------------|-----------------|-----------|--------|
| Part No:          | 014-0061-04     | Low MFD:  | 145.00 |
| Type:             | Start Capacitor | High MFD: | 175.00 |
| User Description: |                 | Volts:    | 220    |

| Run Capacitor     |               |           |       |
|-------------------|---------------|-----------|-------|
| Part No:          | 014-0064-10   | Low MFD:  | 20.00 |
| Type:             | Run Capacitor | High MFD: | 0.00  |
| User Description: |               | Volts:    | 440   |